

THz Measurements, Antennas, and Simulations: From the Past to the Future

FAWAD SHEIKH ¹ (Member, IEEE), ANDREAS PROKSCHA ¹ (Student Member, IEEE),
JOHANNES M. ECKHARDT ² (Student Member, IEEE), TOBIAS DOEKER ² (Student Member, IEEE),
NAVEED A. ABBASI ³ (Member, IEEE), JORGE GOMEZ-PONCE ^{3,4} (Student Member, IEEE),
BENEDIKT SIEVERT ⁵ (Member, IEEE), JAN TARO SVEJDA ⁵ (Member, IEEE),
ANDREAS RENNINGS ⁵ (Member, IEEE), JAN BAROWSKI ⁶ (Senior Member, IEEE),
CHRISTIAN SCHULZ ⁶ (Member, IEEE), ILONA ROLFES ⁶ (Senior Member, IEEE),
DANIEL ERNI ⁵ (Senior Member, IEEE), ANDREAS F. MOLISCH ³ (Fellow, IEEE),
THOMAS KÜRNER ² (Fellow, IEEE), AND THOMAS KAISER ¹ (Senior Member, IEEE)

(Invited Paper)

¹Institute of Digital Signal Processing, University of Duisburg-Essen (UDE), D-47057 Duisburg, Germany

²Institute for Communications Technology, Technische Universität Braunschweig, D-38106 Braunschweig, Germany

³Wireless Devices and Systems Group, University of Southern California, Los Angeles, CA 90089-2560 USA

⁴ESPOL Polytechnic University, Escuela Superior Politécnica del Litoral, ESPOL, Facultad de Ingeniería en Electricidad y Computación,
09-01-5863 Guayaquil, Ecuador

⁵General and Theoretical Electrical Engineering (ATE), Faculty of Engineering, University of Duisburg-Essen, and CENIDE – Center for Nanointegration
Duisburg-Essen, D-47048 Duisburg, Germany

⁶Institute of Microwave Systems, Ruhr University Bochum, D-44801 Bochum, Germany

CORRESPONDING AUTHOR: Fawad Sheikh (e-mail: fawad.sheikh@uni-due.de).

This work was supported in part by Deutsche Forschungsgemeinschaft for Projects M01, M02, M03, M04, C05, and S03, under Project 287022738 TRR 196, in part by the Ministry of Culture and Science of the State of North Rhine-Westphalia (MKW NRW) through Project *terahertz.NRW*, and in part by the Open Access Publication Fund of the University of Duisburg-Essen. The work of Jorge Gomez-Ponce was supported by Foreign Fulbright Ecuador SENESCYT Program. The work of Johannes M. Eckhardt, Tobias Doeker, and Thomas Kürner was supported in part by the Federal Ministry of Education and Research (BMBF), Germany, through 6G Research and Innovation Cluster 6G-RIC under Grant 16KISK031 and in part by German Research Foundation (DFG) under Grant FOR 2863, “Meteracom - Metrology for THz Communications.” The work of Jorge Gomez-Ponce, Naveed A. Abbasi, and Andreas F. Molisch was supported by SRC, DARPA, NSF, NIST, and Samsung Research America through ComSenTer Program.

ABSTRACT In recent years, terahertz (THz) systems have become an increasingly popular area of research thanks to their unique properties such as extremely high data rates towards Tb/s, submillimeter localization accuracy, high resolution remote sensing of materials, and remarkable advances in photonics and electronics technologies. This article traces the progress of THz measurements, antennas and simulations, from historical milestones to the current state of research and provides an outlook on the remaining challenges.

INDEX TERMS Channel modeling, history, MTT 70th Anniversary Special Issue, on-chip antennas, ray-tracing, THz communications, THz measurements and simulations.

I. INTRODUCTION

No doubt, radio waves have been propagating since the beginning of the universe. However, twentieth century marks the era of radio communications initiated by the prediction of electromagnetic (EM) waves from J.C. Maxwell in 1865 based on his EM theory of light owing to the similarity between the two taking into account M. Faraday’s existing experimental works (1831) on EM induction. Later, in the 1880 s, H. Hertz confirmed Maxwell’s theoretical work with multiple

laboratory experiments (original apparatus of Hertz can be seen at the Deutsches Museum in Munich) generating, radiating, and receiving EM waves of 66 cm wavelength in free space.

G. Marconi, inspired by Hertz brought the EM waves (long waves) from the confines of laboratory to the outer world with his epoch-making experiment of transmitting radio signals successfully across the Atlantic ocean in 1901 [1], laying the foundation for long-distance radio communications. Moving

closer to the low THz band (i.e., between 0.1–1 THz), in 1895, J.C. Bose conducted pioneering millimeter-wave (mm-wave) experiments at 60 GHz [2] with radio waves ($\lambda \cong 5$ mm) to ring bells and trigger explosions.

Almost 100 years later from the pioneering work by W. Herschel (1800) in both the visible and near-infrared portions of the EM spectrum, H. Rubens and his colleagues in Berlin advanced their infrared experiments towards the currently termed far-infrared (FIR) or THz region [3]. In 1897, Rubens with E.F. Nichols explicitly acknowledged the existence of a technology gap spanning between the optical and electronic sources of radiation. Later, in 1923, Nichols and J.D. Tear employed the interferometric method for obtaining wavelengths as low as 1.8 mm and finally succeeded in closing the THz gap, defined as the region between 0.1–10 THz, thus joining it to the already explored near-infrared. Along with the advances in the development of THz devices in the last decades, the application of THz waves for modern communication systems became possible. This brief history might perhaps miss some important incidents. Looking ahead at the next decade, the power, peril, and promise of THz technologies will witness even more progressive explorations overcoming the current challenges.

II. THZ CHANNEL MEASUREMENTS

Johannes M. Eckhardt, Tobias Doeker, Thomas Kürner, Naveed A. Abbasi, Jorge Gomez-Ponce and Andreas F. Molisch

First ideas on concepts of THz communications came up almost two decades ago [4], [5], [6]. This has triggered numerous activities on channel measurements and simulations - a necessary initial step when developing a wireless communication system in a new frequency range - at 100 GHz and beyond. Tutorial overviews on these activities are provided for example in [7], [8], [9]. Measurement equipment working at THz frequencies in the early stage was limited mainly to THz Time Domain Spectroscopy (THz-TDS). In this context, THz-TDS has been used to characterize the reflection and scattering properties of materials [10], [11]. These measurements have shown that at wave lengths below 1 mm, surface roughness of typical building materials like concrete and the thickness of paint on a concrete wall - causing a layered structure - significantly influence the scattering behaviour. This is quite different from the observations at lower frequencies, where walls are usually considered as flat surfaces. Based on these findings, ray-tracing has been applied to explore the potential of THz communication systems by simulations [12]. More details on THz simulations are provided in Section IV. Other early works have used first simple THz communication systems that have been built up by discrete components, allowing a rough estimation on potential inter-symbol interference (ISI) in kiosk downloading applications [13]. In outdoor environments, the impact of atmospheric gases in long-path outdoor environments [14] has also been measured by THz-TDS. A comparison of the measured attenuation and achievable bit error rate (BER) in THz and infra-red systems in dust-clouds

and fog has been performed by Su et al. [15], [16] revealing advantages of THz communications in case of low visibility conditions.

With the availability of frequency extenders of vector network analyzer (VNA) at the 100–500 GHz range (and more recently up to 1100 GHz) [17], [18], frequency domain channel sounding has been applied to investigate a multitude of more complex scenarios. In [19] the impact of blocking and diffraction has been described including a comparison of these effects at 60 GHz and 300 GHz. Complete indoor scenarios cover office environments [20], data centers [21], intra-device communications [22], [23], and kiosk downloading [24]. The high path loss and limited dynamic range of the measurement equipment requires the use of high-gain antennas for most of the applications. Rotational units as described in [20] enable automatic spatial scanning at the transmitter (TX) and receiver (RX), thus allowing to derive spatial channel characteristics.

VNA based channel sounding has a major limitation: It can be applied to static scenarios only. Alternative approaches are correlation-based channel sounding (CBCS) working in time domain. In the past years, various CBCS systems have become available [25], [26], [27], [28] allowing either dynamic measurements or reducing the measurement time in static environments significantly. CBCS have been widely used for measurements in various environments such as outdoor environments [27], office environments [26], industrial environments [29], data centers [30], trains [31], automotive [32], and aircrafts [33]. Recently, CBCS have also been used for channel characterisation with regard to the determination of key performance indicator (KPI) for physical layer security such as secrecy capacity [34], [35].

Nowadays, 300 GHz measurement systems are available and allow measurements of more system related KPIs such as bit error rates (BERs). In [36] the impact of diffuse scattering on the BER has been measured. A complementary approach to derive system related KPIs are simulations as described e.g. in [37]. The simulations can be based on either deterministic channel models calibrated from measurements [20] or on stochastic channel models, e.g. [38]. For example, the modeling framework described in [38] has been applied in developing IEEE Std 802.15.3d-2017 [39].

In the following, we will extract key findings on propagation at THz communication systems. Starting with some common insights based on measurement campaigns and simulation from the literature, we will provide more details for scenarios in outdoor environments and data center applications.

A. COMMON INSIGHTS

Measurements reported both in indoor [36], [23], [33], [29], and outdoor [40], [41] environments have shown that THz communications works also in non-line-of-sight (NLoS) situations by exploiting single or even multiple reflection or scattering processes, yielding a reduction of the received power level of compared to line-of-sight (LoS) as low as a few dB. Generally speaking, the pathloss coefficients for NLoS are

in a similar range as those at cm-wave frequencies; however, shadowing is more severe, raising the probability of outage.

In highly reflective environments [23], [24], [33], the delay spread can be considerable - the order of multiple inverse bandwidths - despite the use of directional antennas. Again, this holds true for both indoor and outdoor environments. The measured multipath richness may cause inter-user interference [42], [48]. The use of directional antennas can reduce the multipath richness (though significant multipath might occur even when using directional antennas at both link ends, particularly in outdoor environments). Furthermore, in the presence of non-negligible antenna side lobes, which are hard to avoid for electronically steerable antennas THz [25], [43], multipath richness is further enhanced; in the extreme case of omni-directional antennas, hundreds of multipath component (MPC) have been observed.

THz channels also suffer from significant directional dispersion, which impacts inter-user interference in multi-user environments, due to two effects: i) the strongest paths of an interferer may arrive at the victim RX at such an angle that they fall within the side lobes of the antenna pattern, or ii) the directional dispersion makes (possibly weaker) MPC arrive within the main lobe of the victim RX. Due to the near-far effect, even attenuated interfering MPC can significantly impact the signal-to-interference ratio at a RX; thus channel models need to have high dynamic range. Due to the importance of directional dispersion, channel measurements should generally be double-directional [44], i.e., describe the channel characteristics for each transmit- and receive direction combination.

B. OUTDOOR ENVIRONMENTS

For outdoor environments, the main scenarios envisioned for THz applications are (i) microcells, (ii) hotspots, and (iii) device-to-device (D2D) communications, which have in common that typically links cover distances < 100 m, are in urban environments, and have high anticipated user density; the main difference lies in the height of the “base station”: 10 m in the case of microcells, 3 m to 5 m in the case of hotspots, and 1.5 m in the case of D2D communications.

In addition to these three scenarios, wireless backhaul is also a promising application, but has a significantly different setup (static TX and RX, and mostly static environment, possibly longer distances), and do not require double-directional measurements and thus requires different types of channel measurements.

The first double-directional outdoor measurements were performed in [45]. Though using a VNA, measurements over long distances were made possible by hauling the signal from the receive antenna (and its co-located frequency extender) to the VNA via an RF-over-fiber connection. Measurements used a frequency step of 1 MHz, a bandwidth of 1 GHz, and horn antennas with a beamwidth of 13° . Directional resolution at both TX and RX was achieved by mechanical rotation of the antennas via precision rotors.



FIGURE 1. Map of the outdoor plaza for microcellular environment measurements in [41].

The same setup was subsequently used for extensive (50,000 - 100,000 impulse responses) measurement campaigns in the D2D [40] and the microcellular scenarios [41], see Fig. 1. For both scenarios, the campaigns were performed in an urban environment, with mixtures of street canyons and open squares (plazas/quads or parking lots). In the D2D measurements only the horizontal plane was scanned, while in the microcellular measurements, azimuthal scans were performed for multiple elevation cuts. The same setup was also used for indoor measurements, see [46].

From the measurements, both the directional and the non-directional (omni) pathloss were evaluated. In LoS situations, the pathloss as well as the pathloss coefficient is somewhat smaller than in free space, in line with expectations, and behavior at lower frequencies. In NLoS situations, pathloss is typically higher by about 10 dB to 30 dB compared to free space, though care must be taken in the interpretation of those results: as pointed out in those papers, there is an inherent selection bias caused by the measurement locations chosen such that reasonable receive power could be anticipated; in practice there might be more locations in which complete outage occurs.

Delay dispersion is significant in outdoor scenarios, both for D2D and microcellular environments; a sample can be seen in the lower plot of Fig. 2. In LoS situations, on the order of 3(30) ns is observed for the directional (omni-directional) rms delay spread, while for NLoS, the corresponding values are 2(10) ns and 30(100) ns for microcellular and D2D situations, respectively. When analyzing the number of freely adjustable equalizer taps/Rake fingers to collect 99 % of the energy, values range from 5 to 20 for the chosen directional antennas (13° beamwidth) and bandwidth (1 GHz) [47].

Another important effect observed in these measurements is a strong directional dispersion, which impacts inter-user interference as described in Section II-II-A, with the detailed impact depending on the beamforming algorithm [48]. Energy is coming from multiple clusters that have different directions, see right plot of Fig. 2, with the clusters having different arrival times. Detailed descriptions, sample results, and statistical results for pathloss, delay- and angular dispersion can be found in [40], [41], [47].




FIGURE 2. Angular delay power spectrum (APDS) of outdoor NLoS link, TX3-RX14 for $d_{TX-RX} = 62.6$ m.

Several other measurement campaigns have been performed in recent years, including extensive measurements in an access point (AP) scenario (base station height 4 m) at 140 GHz [49], [50], and a street canyon at 300 GHz [51]. The qualitative insights from those campaigns are similar to the ones mentioned above.

For outdoor environments, blockage by both large and small objects needs to be considered. Large objects might include trucks, cars, and even people. Since most of these objects are essentially impermeable to THz radiation, diffraction around them is the main mechanism. Furthermore, due to the small wavelength, objects such as leaves, lantern masts, etc., which are not significant blockers at cm-wave frequencies, become relevant at THz. Their impact can be analyzed by ray-tracing, or a stochastic-geometry analysis [52], with the two methods showing good agreement.

C. INDOOR ENVIRONMENTS

THz applications can be further imagined in many indoor environments entailing revolutionary benefits. High-speed wireless AP in office premises or wireless D2D communications will influence the modern working world. Directional THz links will bring the mobile machine type communications in industrial environments to the next level and additional wireless THz links in data centers enhancing the flexibility and reconfigurability with comparable data rates to those of fibre connections. Similarly, THz entertainment systems in an aircraft cabin or a high speed train entertain a large number of people thus, upgrading the passenger experience and comfort. The requirements for the mentioned indoor use cases differ from long-distance outdoor applications. Within the paper, our methodology, tool chain, and work flow for the channel characterization of THz communications in indoor scenarios is presented and exemplarily discussed for the data center use case.

Compared to outdoor environments, the dimensions of the indoor measurement setups are smaller, thus reducing the

synchronization and measurement distance between the TX and the RX making systems with ultra-high measurement rate possible. One possible realization of a CBCS system records the channel impulse response (CIR) with a measurement rate of 17,590 CIR/s in a 4×4 multiple-input multiple-output (MIMO) configuration. An ultra-wide band (UWB) module creates an M-sequence allowing a max. access delay of approximately 445 ns with a bandwidth of 8 GHz and serves as an excitation signal. Within the TX frequency extender, the baseband signal is upconverted to a center frequency of 304.2 GHz. All TX and RX are synchronized by a base unit. The same approach is followed for the downconversion in the RX frequency extender before the signal is sampled by analog-to-digital converter (ADC) [25].

The CBCS system measures a spatially limited CIR due to its dependency on highly directive antennas that compensate for the high free space path loss (FSPL) at THz frequencies. Using rotational units with an automatic mechanical steering, a power angular profile (PAP) can be created [53] that enables the processing of an omni-directional CIR [54]. Fig. 3 shows a classical measurement setup in a data center in this case. The equipment is complemented by tripods and a rail system [35].


Aligning the measurement setup with the application-oriented use case, the measurement results are valuable in three different ways: First, various channel parameters are calculated and the propagation is characterized [33]. Second, the measurement data is used for calibration or validation of propagation simulations [31]. Third, the measurement data is directly applied for higher layer simulations of the specific use case.

In this context, measurement campaigns in various indoor environments have revealed the need for scenario-specific channel models at THz frequencies. Referring to the propagation characterization, the data center measurements verify the adequate modeling of FSPL and the importance of reflection and transmission effects that rely on the material properties [30]. Moreover, omni-directional and point-to-point measurements discover significant multipath propagation in all inter-rack measurement setups [8].


III. THZ ON-CHIP ANTENNAS

Benedikt Sievert, Jan Taro Svejda, Andreas Rennings and Daniel Erni


From a historical perspective, antennas and, even more remarkable, J.C. Bose's pioneering sub-THz emitters in 1895 based on a 60 GHz dielectric-lens antenna setup [55] are among the first devices ever developed in the dawn of RF engineering. Since then, antennas have played an essential role in advancing modern RF technology (and in particular the wireless revolution), adapting to increasing demands such as, e.g., smart and controllable functionalities, ultra-widband and multi-band operation, high integration density, shape conformity, including the current access to the THz range [56], [57]. As early as the late 1960 s full-wave computational EM (CEM) simulations, numerical network analysis, and topological optimization [58] had already become the cornerstones



(a) Measurement setup.



(b) Ray-tracing simulation.



(c) PAP of the measurement setup and ray-traced MPCs.

FIGURE 3. Investigations in a data center.

of standard RF design techniques. (Sub-) THz chip antennas can be considered as operating at their physical limit, facing fundamental limitations in gain and radiation efficiency due to the high permittivity of the semiconductor substrates involved. It is therefore not surprising that holistic design concepts [59], such as e.g. those incorporating energy flux from the locally resolved radiation mechanisms in the antenna topology, are receiving increasing attention in current chip antenna research. Efficient (sub-) THz chip antenna optimization in particular invokes thus the full interplay between CEM simulations,




FIGURE 4. The interplay between the modeling of frontend, antenna, and environment is key for state of the art THz systems.

topological optimization and (astonishingly) an equivalent circuit analysis, which will be described in the following. To generate insight into antenna operation beyond the outcome of general purpose CEM solvers, the use of equivalent circuits and other antenna models is motivated shortly. Appropriate models provide a description of port-based parameters, as input impedance or operation frequency. Furthermore, they even enable the determination of polarization, efficiency, and other radiating properties, if an additional far field superposition of fundamental sources (e.g. Huygens sources) is carried out. Compared to the classical full-wave methods mentioned above, for example the equivalent circuit simulation features drastically reduced degrees of freedom, which means that a standard circuit simulator can outperform even high performance full-wave solvers by means of simulation time. As depicted in Fig. 4, modeling the interplay of the antenna with both, sub-THz sources or receivers in the frontend, and the channel describing the environment surrounding the antenna, benefits from both, a simple and insightful antenna representation. On one hand, examples for device-antenna modeling to understand both the THz-generation, as well as desirable operation points, can be found in [60], [61], [62], [63]. Essential system parameters such as, e.g., the equivalent isotropic radiated power (EIRP), can on the other hand be used for channel modeling and system performance evaluation. The physical insight can be increased even further, if dielectric and conductor losses are assigned to the respective antenna parts, such that the effect of each subcircuit on the overall antenna performance is accessible. In this respect, the equivalent circuit model can also be considered as an “epistemic engine” that promotes a deeper understanding into the proper operating mode of chip antennas. As will be shown below, even radiation and near-field coupling can be described and fed into full-wave or ray-tracing solvers.

A thorough overview of different on-chip architectures and utilized structures is presented in [64]. With increasing frequencies above ≈ 100 GHz, the interconnection losses associated with antenna in package or other antenna off-chip solutions increase the attractiveness of on-chip solutions – despite their limitations. These result from the typically lossy and large-permittivity substrates as silicon or indium phosphide for backside radiating antennas, or from a very thin substrate between antenna and on-chip ground for frontside radiating approaches. Here, the electrically small distance




FIGURE 5. Perspective view on an exemplary antenna with the subcircuit models used for equivalent circuit based optimization.

between top- and ground metallization inherently limits both bandwidth and efficiency. With increased manufacturing effort, localized backside etching or large permittivity superstrates and dielectric resonators can partially compensate these limitations. The equivalent circuit modeling described in the following is initially applied to frontside radiating on-chip antennas using an on-chip ground [65]. Generally, the equivalent circuit analysis is a commonly used tool for periodic structures in general [66], even at mm-wave/Sub-THz frequencies [67], [68]. In [69], [70], many design choices and antenna properties of composite right-left handed antennas are derived and predicted from equivalent circuits, however the circuit modeling is not necessarily restricted to antennas. For example, passive reflectors or transmitarrays are described conveniently and insight is generated with and by such circuit models [68], [71].

Given the small distance to the ground plane on-chip, the typically planar antenna implementations are based on classical microstrip antenna designs. For these, prior modeling attempts assigned the radiation mechanism to the so-called radiating edges, as presented in [72], [73]. In detail, it is rather the discontinuity in the microstrip, which radiates [74], [75], than the resulting fringing electric field at the end, however both descriptions enable rough estimations of the resulting radiation [76]. With the approach presented in [77], equivalent circuit elements can be extracted for different local antenna parts, such that the antenna is conveniently described by coupling and cascading subcircuits. The resulting overall equivalent circuit allows for the calculation of current- and voltage distributions, input impedance, radiation efficiency, and even radiated far fields of antennas, as will be shown in the following. An exemplary stripline based antenna with capacitive discontinuities, as initially presented in [78], is depicted in Fig. 5 along with simplified subcircuit models for the different antenna sections. A key motivation for the design of this antenna, which is essentially a modified microstrip patch antenna, was to increase the radiation efficiency by including these discontinuities. With each discontinuity, the antenna length needs to be increased to compensate for

its negative phase shift to obtain a constant operation frequency. By proper design, these discontinuities radiate more power than the additional antenna length dissipates, which means the overall radiation efficiency is increased [78]. The actually used subcircuit models include a rather complex frequency dependence, as e.g. skin-effect losses scale roughly according to $\propto \sqrt{f}$ and radiation losses typically follow a $\propto f^2$ behavior. Furthermore, the distinction between shunt- and series elements within the microstrip context allows for the distinction of current- and voltage-driven phenomena, be it reactive, dissipative or radiative. Lastly, the radiating circuit elements can be associated with corresponding far fields, which are calculated either analytically using appropriate greens functions [79], [80], [81], or numerically using full-wave solvers. Given the voltage or current along these radiating elements from the circuit simulation, a far field superposition can be directly carried out yielding not only port parameters, but even far field antenna parameters. A thorough consideration of the far fields allows for definition of coupling conductances, as already carried out in [82]. The coupling (or mutual) conductances can be combined with the radiation conductances of the single radiators into a conductance matrix, which includes the effect of in- or anti-phase radiation on the radiated power. This even enables the consideration of coupling between radiators in one antenna, as well as antenna-to-antenna coupling in total. With this insight, the position of radiators within the antenna can be optimized to achieve either inherent decoupling or in phase radiation, which ultimately yields a structural optimization of the antenna prototype.

With the hemispherical chip antenna measurement setup from [83], the radiated far field of the chip antenna from [77] is recorded. The measured far field is compared to the far field superimposed using fundamental radiation sources and the results from the circuit simulation. Whereas the superposition of fundamental sources only yields the directivity, the mismatch using the input impedance and the radiation efficiency using the separation of dissipative and radiative losses can be obtained from the equivalent circuit resulting in a description of the realized gain. It should be noted that the (expected) overall small gain values result from the small aperture of the on-chip antenna, which has been characterized without any aperture-increasing lens or reflector. The comparison of measurement and circuit model prediction is depicted in Fig. 6, and the agreement is, given the high complexity of on-chip measurements [84] and the simplicity of the circuit, very good. Here, the good agreement is essentially achieved by considering the radiators mutual coupling. The only limitation lies within the on-chip measurement, namely minor interference effects at the on-wafer probe [85] resulting in small undulations along the θ -axis, and a shadowed region caused by the probe [86] for $\theta < 6^\circ$. Finally, this antenna measurement closes the design loop – starting from an antenna concept, which is numerically analyzed with full-wave solvers, resulting in an insightful and simpler circuit representation, to a fabricated prototype, which meets the design specifications.




FIGURE 6. Realized gain measurement of the antenna prototype in [77] compared to the estimation of the corresponding equivalent circuit (EC) model in \vec{E} - and \vec{H} -plane at 290 GHz (a) and micrograph of the antenna prototype (b).

IV. THZ RAY-TRACING SIMULATIONS

Fawad Sheikh, Andreas Prokscha, Thomas Kaiser, Jan Barowski, Christian Schulz, Ilona Rolfes, Johannes M. Eckhardt, Tobias Doeker and Thomas Kürner

A. RADIO CHANNEL MODELS

A new wireless communication system inevitably relies on a well conceived radio channel wherein radio waves carry the signals or information. Radio waves are typically produced by an *antenna*. The undesirable effects caused by these radio channels impact the radio system design. Hence, accurate channel modeling whereby a physical understanding of these channels with their corresponding mathematical modeling is inevitable for improvising the channel behaviour and consequently optimize the system performance. By excluding the effect of the antenna from the channel model results in a *propagation channel* [44], [87]. The aim of these channel models is to efficiently yield accurate coverage predictions on radio wave propagation key statistics namely, CIRs, received signal strengths, angular spreads, delays of direct/indirect paths, electric as well as magnetic field strengths, and interference measures. Typically, the channel model type shows critical reliance on carrier frequency, bandwidth, type of environment and system under consideration. The simplest propagation model for free space radio propagation published in 1946 is the Friis equation [88], with a single unobstructed communication path. However, the Friis model yields useful results only in the *far field* region, being useful for satellite and LoS microwave links. Contrarily, the other NLoS propagation mechanisms such as *reflection*, *scattering*, and *diffraction* collectively termed as *multipath* perform in the absence of LoS links. MPC represents the most serious potential problem in many radio channels, i.e., a source of selective fading and ISI. Adding to it, the wide-band nature further complicates this aspect of channel modeling [89].

In 1956, the classical a priori based simulation approach initially suggested by Turin in a technical report [90] and a classical paper [91] which was then applied to the urban channel [92] marks the foremost work in impulse response modeling of the multipath fading channels. This followed the development of RAKE receiver for multipath channels [93].

Turin's model was later modified by Hashemi [94], [95], Ganesh and Pahlavan [96], Suzuki [97], Saleh and Valenzuela [98], and Rappaport et al. [99]. However, owing to the simplistic nature of this model, some environment related information cannot be incorporated easily without further measurements. Hence, novel simulation models including more site-specific information are developed. Moreover, simulating the propagation channel with ray-tracing can prior to the installation of the wireless system predict its successful operation, and in large part, replace measurements.

B. RAY-TRACING: SUB-GHZ TO LOW-THZ BAND

Ray-tracing, a well known deterministic propagation channel modeling method, from the CEM family among others such as, the finite element method (FEM), the finite-difference time domain (FDTD), the method of moments (MoM), predicts and describes the behaviour of EM waves when they come into contact with physical objects. At lower frequencies, the field of cellular technology, in particular, has greatly benefited from the CEM simulation techniques helping scientists to develop better antennas and communication systems. However, a major drawback of these techniques, in general, is that they require intensive computations along with a detailed description and information of the simulation scenario. Such limitations and restrictions tend to affect the accuracy of their results.

Ray-tracing methods are based on Geometrical Optics (GO) which solve the Maxwell's equations in *high frequency* range. Due to their high frequency approximation, they are not highly dependent on a large computer memory and hence, can solve, complex, 3D, and electrically large problems on modern computers [100]. In contrast, the numerical methods (FEM, FDTD, MoM etc.) are ruled out for very short wavelengths ≤ 5 mm when quantifying the behavior of the EM field in electrically large propagation environments [101]. By far, ray-tracing is highly environment-specific and its accuracy is heavily dependent on the availability of the materials and topographical database utilized in the modeling [102]. Since 1990's, ray-tracing algorithm has been developed based on the theory of GO [103], [104]. The shooting and bouncing ray (SBR) method has an edge over other ray-tracing methods with the advantage of accelerated simulation time [100], [105]. This SBR method, foremost developed for computation of radar cross section (RCS) encompasses three steps, namely, ray launching, ray tracing, and ray reception [100].

For many years, ray-tracing has been at the forefront in channel modeling for outdoor [106]–[110], in-building [111], and indoor [112]–[114] environments in the lower frequency range. Additionally, ray-tracing models for 60 GHz systems have been previously reported in the literature [101], [115], [116]. However, a decade ago, every single commercially available ray-tracing tool failed to respond to the need for THz propagation modeling [11]. The reason being the absence of distinct THz propagation mechanisms such as diffuse scattering (non-specular reflections)

caused by rough surfaces [117]. A handful lot from the THz community fulfilled this void by developing the ray-tracing algorithm (RTA) incorporating this critical propagation mechanism [118]–[120]. The attenuation due to surface roughness in a specular direction of reflection can be approximated using the already validated Rayleigh-Rice (R-R) approach [121]. Beckmann-Kirchhoff (B-K) approach, though primarily opted for the diffuse scattering in non-specular direction accounts for diffuse scattering impact in specular direction of reflection as well [118]. Both the aforementioned models employ the average roughness parameter (i.e., the standard deviation height σ_h) and hence, actual random deviations from the 3D surface topography are missing. In our previous works [122]–[124], tailor-made rough surfaces with known statistical parameters of surface roughness are integrated along with their real 3D surface topography to enhance the model further assisting in the comparative study of random and non-random rough surfaces.

When designing very high speed wireless links that offer 100 Gb/s and beyond, high-gain antennas such as horns may be favored particularly for point-to-point THz communications. The horns from measurement setups can be designed using CST MWS simulation software. The 3D radiation patterns of CST MWS designed horn may then be exported for ray-tracer simulations [125]. This implies that ϕ - and θ -values for E- and H-planes at defined constant angle spacing or interval can be exported as ASCII data. Since many combinations are possible, in our previous work [123], we have explored the right ϕ/θ step size which is in good agreement with the measurements. This information can thus, assist in the ray-tracer calibrations at THz band frequencies when employing single antenna or antenna array patterns. Interestingly, horn antennas have a divergent beam (i.e., in their spatial structure unless collimating lenses are used) where the beam spot size gets larger at farther distances. The beam spot diameter from high-gain horn antenna with beam divergence holds a pivotal position for channel modeling in THz communications. For instance, larger beam spot size tends to reduce misalignment losses [17]. Moreover, the increase in beam spot diameter generates unwanted and measurement sophisticated reflections at local scatterers, reflectors or even at the measurement devices, thereby resulting in the so called *ping pong effect* [126].

Previously, a human body model with low complexity is employed to evaluate its influence on channel characterization in blockage situations with the help of ray-tracing simulations. The human is predominantly portrayed as a cylinder shaped model with additional spheres or prisms representing body parts like heads, arms and legs thus enhancing it to resemble the real shape of humans [127], [128], as can be seen in Fig. 7. To some degree, these former approaches are sufficient, however, they may fail to replicate the realistic movements when exploiting mobile THz channels. In our previous work [129], we have employed the quaternion based inertial measurement unit (IMU) data to record human kinematics and the acquired data is then embedded into a male digital twin for simulating




FIGURE 7. Illustration of the evolution of 3D human body models for ray-tracing simulations from previous (left) to newly introduced, more detailed and gender-related digital twins for 1.80 m male and 1.63 m female (right).




FIGURE 8. Illustration of the bone and muscle layers with the connective tissues on 3D human body model, figure adapted from [133].

real joint movements. This male digital twin represents: i) an accurate 3D human body model with sophisticated details (i.e., hand, fingers, nose and hairs), and ii) its clothing keeping in view the corresponding frequency-dependent dielectric properties of the fabrics, see [130]. In future, the aim is to explore muscle dynamics (*cf.* Fig. 8) employing CEM simulation techniques in supporting the exoskeleton technology further and thus, progressing human capabilities to go beyond previous research.

In fact, the frequencies of THz communications being closer to the frequencies of light, benefit deterministic modeling approaches for channel predictions. Considering modern high-performance computing and specialized algorithms, even bigger and complex scenarios can be simulated [131]. The ray-tracing, thus offers results in three aspects for THz communications: First, channel predictions in terms of CIR itself. Second, angular information of the angle of departure (AoD) and of the angle of arrival (AoA) useful for the evaluation of algorithms in device discovery [132]. Third, different types of map predictions [34]. As aforementioned, a prerequisite for ray-tracing is a 3D model of the environment, often called "digital twin," that contains information regarding the material parameters. Fig. 3(b) illustrates the data center and the MPCs of the corresponding setup. The ray-traced MPCs in the data center model depicted in Fig. 3(c) as red crosses together with the PAP of the respective measurement pinpoint that the simulations match very well in terms of angle and

delay, whereas the modeling of the amplitude deserves closer attention. In addition, the accuracy of the positioning of the objects is more important than the level of detail for the objects themselves [37].

C. THZ NEAR-FIELD AND MULTI-SCALE SIMULATIONS

Especially when tackling the THz-region with deterministic channel modeling approaches such as ray-tracing, the effort in accurate modeling increases dramatically. In addition to the increasing complexity of geometric models that is needed because of the shorter wavelength, THz communication and sensing systems usually aim at utilizing huge bandwidths demanding wideband material models as well [134]. Therefore, accurate ultra-wideband material characterization [135], i.e. determination of the relative permittivity as well as the material's loss tangent is necessary even before simulations can start. Furthermore, also the dispersion of typical air has to be considered [136].

Once the environment models are available, we can consider the different dimensions and scales that are relevant to the wave propagation within the scenario. On the one hand, there usually are large free space areas that have only minor influence on the transmitted signal, i.e. the propagating ray. In these areas, the wave propagation can be considered as being affected by *large scale* effects such as free space attenuation, dispersion or the interaction (i.e. reflection and transmission) with objects that are large and sufficiently smooth with respect to the wavelength [137]. On the other hand there are plenty of possible wave interactions in the THz-range that affect the wave by *small scale* effects, demanding higher accuracy in the modeling. These may for example be caused by rough surfaces and in-homogeneous media that allow for a relevant penetration and that are not suitable for an average description by e.g. Kirchhoff parameters [138]. In this context also highly deterministic surfaces such as intelligent reflective surfaces (IRS) have to be mentioned [139]. Furthermore, scattering from small objects, complex diffracting objects, and all interactions that have to be considered by near-field methods have to be investigated on a *smaller scale* that is more detailed.

Near-field methods are usually needed in simulations used in THz imaging or when it comes to extremely large radiating (actively or passively like IRS) structures that cause very large Fraunhofer distances [140]. Since an efficient simulation is not possible anymore, if the high level of detail from these small scale regions is transferred to the large scale domain as well, a differentiation of the total simulation domain into several sub-domains that are considered either by large or small scale methods is necessary [141]. Therefore a decoupling of these sub-domains is of high importance and can be realized offline based on precalculated results or online with detailed but efficient simulation methods, such as physical optics (PO) [142], [143], [144]. The interfaces between these domains are a research objective on its own and can be related to full-wave near field methods, dominant mode considerations, or even far field quantities such as (bistatic) RCS and gain.

However, the aforementioned scenarios have in common that plane wave assumptions usually do not hold anymore, making things complex and interesting at the same time. In these scenarios the curvature of the wavefront and the amplitude distribution are of high importance. Due to the short wavelength and the according large free space path loss, electrical large apertures that result in strongly focused fields and beams are very common in the upper mmWave and THz regions [145]. Therefore, full wave methods such as FDTD [146] may be employed for detailed analysis. Of course, the needed volume discretization quickly exceeds computationally efficient scales. Surface related methods such as the MoM [147] may be used for large scattering structures but not for complete scenarios, as well. In the end, asymptotic methods like the PO still offer the opportunity to relax far field assumptions [148], [149], while calculating the propagation channel on explicitly a predefined path. In contrast to MoM (solving an inverse model), a forward model is employed in PO, that allows to tune the granularity of the simulation by manually selecting the propagation paths *a priori*. By suitable extensions [150], PO also offers the opportunity to incorporate sub-surface features and multi-layer dielectrics.

An elegant method to describe these focused fields and propagation scenarios that rely on few dominant modes (i.e. beams) are complex source beams (CSB), sometimes also called complex origin beams. A CSB describes a Gaussian beam [151], [152], as it is used in an optical system. The compact mathematical formulation is based on the well known scalar Green's function of free space [153] in 3-dimensional space

$$G(\vec{r}, \vec{r}_0) = \frac{\exp(-jk|\vec{r} - \vec{r}_0|)}{4\pi|\vec{r} - \vec{r}_0|} \quad (1)$$

with k being the wavenumber, \vec{r}_0 the wave's origin and \vec{r} the considered point. In order to describe a Gaussian beam, additional information on the direction and the beam-waist, i.e. the opening angle of the beam is needed. This is included by transforming the origin point \vec{r}_0 from \mathbb{R}^3 to \mathbb{C}^3 , whereas the imaginary part of \vec{r}_0 yields this information. Using the Gaussian beam waist w_0 , the Rayleigh distance of the beam is given by

$$z_R = \frac{kw_0^2}{2}. \quad (2)$$

Thus a Gaussian beam of width w_0 originating in $\vec{v} = (x_0, y_0, z_0)^T$ steering into the direction $\vec{u} = (u_x, u_y, u_z)^T$ (with $|\vec{u}| = 1$) can be described by its complex source point

$$\vec{r}_0 = \vec{v} - jz_R\vec{u}, \quad (3)$$

offering a compact and elegant description for focused beams in the near field region of the source. The scalar field magnitude of different CSB for a signal source of 500 GHz is presented in Fig. 9.

With respect to THz-propagation models, these representation comes with the advantage that beam divergence is taken into account at a higher level of detail than classical far field models and is therefore more accurate when it comes to either




FIGURE 9. Field magnitudes from different complex source beams (CSB) differing by their beam waist parameter: (a) $w_0 = 0.5\lambda$, (b) $w_0 = \lambda$, and (c) $w_0 = 5\lambda$, demonstrating e.g. the ability to describe radiation from extended source areas (e.g. antenna arrays). The beams steer towards the positive x -axis, therefore the field magnitude in the negative x -halfplane is nearly zero. The red lines indicate the full width half maximum (FWHM) region.




FIGURE 10. A possible concept for a multi-scale THz propagation channel simulator, handling the coupling of several remote domains (i.e. the relations of radiated, incident, and scattered fields in these) by generalized scattering matrices (GSM), figure adapted from [154].

extremely large frequencies, large structures, i.e. high gain structures, or short distances [154]. If one is aiming at multi-scale simulations of the THz regime, taking multiple large- and small-scale domains into account, CSBs provide a compact yet powerful tool, as e.g. basis functions, to describe the fields within and the coupling between several domains. Combining this with generalized scattering matrix representation of the several subdomains and efficient PO based propagation modeling (*cf.* Fig. 10), it offers a set of tools for calculating the propagation channel throughout the complete simulation environment [155].




FIGURE 11. BER based on link level simulations in the data center environment for a BPSK transmission with root-raised cosine (RRC) pulse and $B_{ch} = 12.96$ GHz.

D. SYSTEM AND LINK LEVEL SIMULATIONS

The development of novel communication systems is nowadays strongly based on the prediction of the system performance and the testing of algorithms via simulations. A physical layer simulator that is based on a modular block structure enables single-carrier transmissions according to IEEE Std 802.15.3d and multi-carrier transmissions [37]. This way, the influence of the measured and simulated channel and the impact of the configuration parameters on the system can be examined. Fig. 11 shows the BER of a BPSK transmission with root-raised cosine (RRC) pulse for various coding schemes and distances from 0.69 m up to 16.5 m between TX and RX of a top-of-rack scenario in the data center model presented in Section II C. Higher order modulation schemes proved to be challenging due to currently limited TX power. For an increasing number of THz AP, multipath propagation in combination with side lobes of steerable antenna arrays cause ISI or inter-user interference that severely limit the performance. Thus, hardware and algorithm designers have to address side lobe suppression and multiplexing techniques [42].

FUTURE CHALLENGES

Most of the channel measurements in the THz range reported so far in the literature have been performed in static environments. Future applications, for example in railway [157] and automotive environments [158] require measurements in dynamic environments taking mobility into account. This becomes even more important with the advent of joint communications and sensing (JCAS) applications, wherein the communications and radars in automotive applications may operate at THz frequencies. Here, the use of static measurements for the calibration of ray-tracer prior to simulating the dynamic environments might be a promising approach. New technologies like intelligent reflecting surfaces (IRS) and massive MIMO with or without the combination of mobility encompass further challenges in THz measurement, antennas, and simulation research.

ACKNOWLEDGMENT

This work did not involve human subjects or animals in its research.

REFERENCES

- [1] W. Gordon, "A hundred years of radio propagation," *IEEE Trans. Antennas Propag.*, vol. 33, no. 2, pp. 126–130, Feb. 1985.
- [2] D. T. Emerson, "The work of jagadis chandra bose: 100 years of millimeter-wave research," *IEEE Trans. Microw. Theory Techn.*, vol. 45, no. 12, pp. 2267–2273, Dec. 1997.
- [3] F. F. Sizov, "Brief history of THz and IR technologies," *Semicond. Phys., Quantum Electron. Optoelectron.*, vol. 22, no. 1, pp. 67–79, Mar. 2019.
- [4] R. Piesiewicz et al., "Short-range ultra-broadband terahertz communications: Concepts and perspectives," *IEEE Antennas Propag. Mag.*, vol. 49, no. 6, pp. 24–39, Dec. 2007.
- [5] J. Federici and L. Moeller, "Review of terahertz and subterahertz wireless communications," *J. Appl. Phys.*, vol. 107, no. 11, Jun. 2010, Art. no. 111101.
- [6] T. Kleine-Ostmann and T. Nagatsuma, "A review on terahertz communications research," *J. Infrared, Millimeter, THz Waves*, vol. 32, no. 2, pp. 143–171, Jan. 2011.
- [7] C. Han et al., "Terahertz wireless channels: A holistic survey on measurement, modeling, and analysis," *IEEE Commun. Surv. Tut.*, vol. 24, no. 3, pp. 1670–1707, third quarter 2022.
- [8] T. Kürner, D. M. Mittleman, and T. Nagatsuma, *THz Communications: Paving the Way Towards Wireless Tbps*. Cham, Switzerland: Springer, 2022.
- [9] T. S. Rappaport, K. A. Remley, C. Gentile, A. F. Molisch, and A. Zajic, *Radio Propagation Measurements and Channel Modeling: Best Practices for Millimeter-Wave and Sub-Terahertz Frequencies*. Cambridge, U.K.: Cambridge Univ. Press, 2022.
- [10] C. Jansen, R. Piesiewicz, D. Mittleman, T. Kürner, and M. Koch, "The impact of reflections from stratified building materials on the wave propagation in future indoor terahertz communication systems," *IEEE Trans. Antennas Propag.*, vol. 56, no. 5, pp. 1413–1419, May 2008.
- [11] C. Jansen et al., "Diffuse scattering from rough surfaces in THz communication channels," *IEEE Trans. THz Sci. Technol.*, vol. 1, no. 2, pp. 462–472, Nov. 2011.
- [12] R. Piesiewicz, M. Jacob, M. Koch, J. Schoebel, and T. Kürner, "Performance analysis of future multigigabit wireless communication systems at THz frequencies with highly directive antennas in realistic indoor environments," *IEEE J. Sel. Topics Quantum Electron.*, vol. 14, no. 2, pp. 421–430, Mar./Apr. 2008.
- [13] S. Priebe, C. Jastrow, M. Jacob, T. Kleine-Ostmann, T. Schrader, and T. Kürner, "Channel and propagation measurements at 300 GHz," *IEEE Trans. Antennas Propag.*, vol. 59, no. 5, pp. 1688–1698, May 2011.
- [14] E.-B. Moon, T.-I. Jeon, and D. R. Grischkowsky, "Long-path THz-TDS atmospheric measurements between buildings," *IEEE Trans. THz Sci. Technol.*, vol. 5, no. 5, pp. 742–750, Sep. 2015.
- [15] K. Su, L. Moeller, R. B. Barat, and J. F. Federici, "Experimental comparison of terahertz and infrared data signal attenuation in dust clouds," *J. Opt. Soc. Amer. A, Opt., Image Sci., Vis.*, vol. 29, no. 11, pp. 2360–2366, Nov. 2012.
- [16] K. Su, L. Moeller, R. B. Barat, and J. F. Federici, "Experimental comparison of performance degradation from terahertz and infrared wireless links in fog," *J. Opt. Soc. Amer. A, Opt., Image Sci., Vis.*, vol. 29, no. 2, pp. 179–184, Feb. 2012.
- [17] F. Sheikh, Y. Zantah, M. Al-Hasan, I. Mabrouk, N. Zarifeh, and T. Kaiser, "Horn antenna misalignments at 100, 300, 400, and 500 GHz in close proximity communications," in *Proc. IEEE Int. Symp. Antennas Propag. USNC-URSI Radio Sci. Meeting*, Singapore, 2021, pp. 449–450.
- [18] F. Sheikh, Y. Zantah, N. Zarifeh, and T. Kaiser, "Channel measurements of 0.9–1.1 THz wireless links using VNA extenders," in *Proc. 46th Int. Conf. Infrared, Millimeter, THz Waves*, Chengdu, China, 2021, pp. 1–2.
- [19] M. Jacob, S. Priebe, R. Dickhoff, T. Kleine-Ostmann, T. Schrader, and T. Kürner, "Diffraction in mm and sub-mm wave indoor propagation channels," *IEEE Trans. Microw. Theory Techn.*, vol. 60, no. 3, pp. 833–844, Mar. 2012.
- [20] S. Priebe, M. Kannicht, M. Jacob, and T. Kürner, "Ultra broadband indoor channel measurements and calibrated ray tracing propagation modeling at THz frequencies," *J. Commun. Netw.*, vol. 15, no. 6, pp. 547–558, Dec. 2013.
- [21] C.-L. Cheng and A. Zajic, "Characterization of propagation phenomena relevant for 300 GHz wireless data center links," *IEEE Trans. Antennas Propag.*, vol. 68, no. 2, pp. 1074–1087, Feb. 2020.
- [22] S. Kim and A. Zajic, "Characterization of 300-GHz wireless channel on a computer motherboard," *IEEE Trans. Antennas Propag.*, vol. 64, no. 12, pp. 5411–5423, Dec. 2016.
- [23] A. Fricke, T. Kürner, M. Achir, and P. Le Bars, "A model for the reflection of terahertz signals from printed circuit board surfaces," in *Proc. 11th Eur. Conf. Antennas Propag.*, Paris, France, 2017, pp. 711–715.
- [24] D. He et al., "Stochastic channel modeling for kiosk applications in the terahertz band," *IEEE Trans. THz Sci. Technol.*, vol. 7, no. 5, pp. 502–513, Sep. 2017.
- [25] S. Rey, J. M. Eckhardt, B. Peng, K. Guan, and T. Kürner, "Channel sounding techniques for applications in THz communications: A first correlation based channel sounder for ultra-wideband dynamic channel measurements at 300 GHz," in *Proc. 9th Int. Congr. Ultra Modern Telecommun. Control Syst. Workshops*, Munich, Germany, 2017, pp. 449–453.
- [26] D. Dupleich, R. Müller, S. Skoblikov, M. Landmann, G. D. Galdo, and R. Thomä, "Characterization of the propagation channel in conference room scenario at 190 GHz," in *Proc. 14th Eur. Conf. Antennas Propag.*, Copenhagen, Denmark, 2020, pp. 1–5.
- [27] M. Schmieder et al., "THz channel sounding: Design and validation of a high performance channel sounder at 300 GHz," in *Proc. IEEE Wireless Commun. Netw. Conf. Workshops*, Seoul, Korea, 2020, pp. 1–6.
- [28] D. Shakya, T. Wu, M. E. Knox, and T. S. Rappaport, "A wideband sliding correlation channel sounder in 65 nm CMOS: Evaluation board performance," *IEEE Trans. Circuits Syst. II, Exp. Briefs*, vol. 68, no. 9, pp. 3043–3047, Sep. 2021.
- [29] A. Schultze, M. Schmieder, S. Wittig, H. Klessig, M. Peter, and W. Keusgen, "Angle-resolved THz channel measurements at 300 GHz in an industrial environment," in *Proc. IEEE 95th Veh. Technol. Conf.*, Helsinki, Finland, 2022, pp. 1–7.
- [30] J. M. Eckhardt, T. Doeker, S. Rey, and T. Kürner, "Measurements in a real data centre at 300 GHz and recent results," in *Proc. 13th Eur. Conf. Antennas Propag.*, Krakow, Poland, 2019, pp. 1–5.
- [31] K. Guan et al., "Channel sounding and ray tracing for intrawagon scenario at mmWave and sub-mmwave bands," *IEEE Trans. Antennas Propag.*, vol. 69, no. 2, pp. 1007–1019, Feb. 2021.
- [32] J. M. Eckhardt, V. Petrov, D. Moltchanov, Y. Koucheryavy, and T. Kürner, "Channel measurements and modeling for low-terahertz band vehicular communications," *IEEE J. Sel. Areas Commun.*, vol. 39, no. 6, pp. 1590–1603, Jun. 2021.
- [33] T. Doeker, J. M. Eckhardt, and T. Kürner, "Channel measurements and modeling for low terahertz communications in an aircraft cabin," *IEEE Trans. Antennas Propag.*, early access, Jul. 20, 2022, doi: [10.1109/TAP.2022.3191218](https://doi.org/10.1109/TAP.2022.3191218).
- [34] C. Herold, T. Doeker, J. M. Eckhardt, and T. Kürner, "Investigation of eavesdropping opportunities in a meeting room scenario for THz communications," in *Proc. 16th Eur. Conf. Antennas Propag.*, Madrid, Spain, 2022, pp. 1–5.
- [35] C. Herold, T. Doeker, and T. Kürner, "Measurements at 300 GHz in eavesdropping scenarios and first results," in *Proc. 5th Int. Workshop Mobile THz Syst.*, Duisburg, Germany, 2022, pp. 1–4.
- [36] J. Ma, R. Shrestha, W. Zhang, L. Moeller, and D. M. Mittleman, "Terahertz wireless links using diffuse scattering from rough surfaces," *IEEE Trans. THz Sci. Technol.*, vol. 9, no. 5, pp. 463–470, Sep. 2019.
- [37] J. M. Eckhardt, C. Herold, B. K. Jung, N. Dreyer, and T. Kürner, "Modular link level simulator for the physical layer of beyond 5G wireless communication systems," *Radio Sci.*, vol. 57, no. 2, Feb. 2021, Art. no. e2021RS007395.
- [38] B. Peng, K. Guan, A. Kuter, S. Rey, M. Patzold, and T. Kürner, "Channel modeling and system concepts for future terahertz communications: Getting ready for advances beyond 5G," *IEEE Veh. Technol. Mag.*, vol. 15, no. 2, pp. 136–143, Jun. 2020.
- [39] V. Petrov, T. Kürner, and I. Hosako, "IEEE 802.15.3 d: First standardization efforts for sub-terahertz band communications toward 6 G," *IEEE Commun. Mag.*, vol. 58, no. 11, pp. 28–33, Nov. 2020.

- [40] N. A. Abbasi et al., "THz band channel measurements and statistical modeling for urban D2D environments," *IEEE Trans. Wireless Commun.*, early access, Jun. 28, 2022, doi: [10.1109/TWC.2022.3184929](https://doi.org/10.1109/TWC.2022.3184929).
- [41] N. A. Abbasi et al., "THz band channel measurements and statistical modeling for urban microcellular environments," 2021, *arXiv:2112.01770*.
- [42] J. M. Eckhardt, C. Herold, B. Friebel, N. Dreyer, and T. Kürner, "Realistic interference simulations in a data center offering wireless communication at low terahertz frequencies," in *Proc. Int. Symp. Antennas Propag.*, Taipei, Taiwan, 2021, pp. 1–2.
- [43] L. G. Guerrero et al., "Design and fabrication of sub-THz steerable photonic transmitter 1×4 array for short-distance wireless links," in *Proc. Joint Eur. Conf. Netw. Commun. 6G Summit*, Porto, Portugal, 2021, pp. 490–495.
- [44] M. Steinbauer, A. F. Molisch, and E. Bonek, "The double-directional radio channel," *IEEE Antennas Propag. Mag.*, vol. 43, no. 4, pp. 51–63, Aug. 2001.
- [45] N. A. Abbasi et al., "Double directional channel measurements for THz communications in an urban environment," in *Proc. ICC IEEE Int. Conf. Commun.*, Dublin, Ireland, 2020, pp. 1–6.
- [46] J. Gomez-Ponce et al., "Impact of common reflecting and absorbing building materials on THz multipath channels," *Radio Sci.*, vol. 57, no. 2, pp. 1–16, Feb. 2022.
- [47] J. Gomez-Ponce, N. A. Abbasi, A. E. Willner, C. J. Zhang, and A. F. Molisch, "Directionally resolved measurement and modeling of THz band propagation channels," *IEEE Open J. Antennas Propag.*, vol. 3, pp. 663–686, Jun. 2022.
- [48] J. Gomez-Ponce, N. A. Abbasi, Z. Cheng, and A. F. Molisch, "Directional characteristics of THz outdoor channels - measurement and system performance implications," in *Proc. 5th Asilomar Conf. Signals, Syst., Comput.*, Pacific Grove, CA, USA, 2021, pp. 658–663.
- [49] S. Ju, Y. Xing, O. Kanhere, and T. S. Rappaport, "Sub-terahertz channel measurements and characterization in a factory building," in *Proc. ICC IEEE Int. Conf. Commun.*, Seoul, Republic of Korea, 2022, pp. 2882–2887.
- [50] Y. Xing and T. S. Rappaport, "Millimeter wave and terahertz urban microcell propagation measurements and models," *IEEE Commun. Lett.*, vol. 25, no. 12, pp. 3755–3759, Dec. 2021.
- [51] F. Urdi, A. Schultze, W. Keusgen, M. Peter, and T. Eichler, "Angle-resolved THz channel measurements at 300 GHz in an outdoor environment," in *Proc. IEEE Int. Conf. Commun. Workshops*, Montreal, QC, Canada, 2021, pp. 1–7.
- [52] P. Koivumäki, A. F. Molisch, and K. Haneda, "Line-of-sight probability in cluttered urban microcells: Analyses using poisson point process and point cloud," *IEEE Trans. Antennas Propag.*, vol. 70, no. 3, pp. 2161–2173, Mar. 2022.
- [53] W. Fan, F. Zhang, Z. Wang, O. K. Jensen, and G. F. Pedersen, "On angular sampling intervals for reconstructing wideband channel spatial profiles in directional scanning measurements," *IEEE Trans. Veh. Technol.*, vol. 69, no. 11, pp. 13910–13915, Nov. 2020.
- [54] J. Liang, J. Lee, M.-D. Kim, and X. Yin, "Synthesis techniques of narrow beam-width directional antenna measurements for millimeter-wave channel characterization," in *Proc. Int. Conf. Inf. Commun. Technol. Convergence*, Jeju, Korea, 2015, pp. 689–693.
- [55] T. K. Sarkar and D. L. Sengupta, "An appreciation of j. c. bose's pioneering work in millimeter waves," *IEEE Antennas Propag. Mag.*, vol. 39, no. 5, pp. 55–63, Oct. 1997.
- [56] I. Malhotra and G. Singh, *Terahertz Antenna Technology for Imaging and Sensing Applications*. Cham, Switzerland: Springer Nature, 2021.
- [57] S. Li, Z. Zhang, B. Rupakula, and G. M. Rebeiz, "An eight-element 140 GHz wafer-scale phased-array transmitter with 32 dBm peak EIRP and > 16 Gbps 16QAM and 64QAM operation," in *Proc. IEEE MTT-S Int. Microw. Symp.*, Atlanta, GA, USA, 2021, pp. 795–798.
- [58] J. W. Bandler, "Optimum noncommensurate stepped transmission-line transformers," *Electron. Lett.*, vol. 4, no. 11, pp. 212–213, May 1968.
- [59] G. Hans Schantz, *The Art and Science of Ultrawideband Antennas*, 2nd ed. Norwood, MA, USA: Artech House, 2015.
- [60] S. Takahagi, H. Shin-ya, K. Asakawa, M. Saito, and M. Suhara, "Equivalent circuit model of triple-barrier resonant tunneling diodes monolithically integrated with bow-tie antennas and analysis of rectification properties towards ultra wideband terahertz detections," *Jpn. J. Appl. Phys.*, vol. 50, no. 1S2, Jan. 2011, Art. no. 01BG01.
- [61] K. Okada, K. Kasagi, N. Oshima, S. Suzuki, and M. Asada, "Resonant-tunneling-diode terahertz oscillator using patch antenna integrated on slot resonator for power radiation," *IEEE Trans. THz Sci. Technol.*, vol. 5, no. 4, pp. 613–618, Jul. 2015.
- [62] I. Malhotra, P. Thakur, S. Pandit, K. R. Jha, and G. Singh, "Analytical framework of small-gap photoconductive dipole antenna using equivalent circuit model," *Opt. Quant. Electron.*, vol. 49, no. 10, p. 334, Sep. 2017.
- [63] V. Rathinasamy, R. R. Thipparaju, E. N. F. Boby, and S. Mondal, "Numerical investigation and circuit analysis of interdigitated photoconductive antenna for terahertz applications," *Opt. Quant. Electron.*, vol. 54, no. 4, p. 239, Mar. 2022.
- [64] M. de Kok, A. B. Smolders, and U. Johannsen, "A review of design and integration technologies for D-band antennas," *IEEE Open J. Antennas Propag.*, vol. 2, pp. 746–758, Jun. 2021.
- [65] A. Shami, K. N. Salama, E. A. Soliman, and S. Sedky, "On-chip antenna: Practical design and characterization considerations," in *Proc. 14th Int. Symp. Antenna Techn. Appl. Electromagn. Amer. Electromagn. Conf.*, Ottawa, ON, Canada, 2010, pp. 1–4.
- [66] S. Otto, A. Rennings, K. Solbach, and C. Caloz, "Transmission line modeling and asymptotic formulas for periodic leaky-wave antennas scanning through broadside," *IEEE Trans. Antennas Propag.*, vol. 59, no. 10, pp. 3695–3709, Oct. 2011.
- [67] A. Alex-Amor, F. Mesa, A. Palomares-Caballero, C. Molero, and P. Padilla, "Exploring the potential of the multi-modal equivalent circuit approach for stacks of 2-D aperture arrays," *IEEE Trans. Antennas Propag.*, vol. 69, no. 10, pp. 6453–6467, Oct. 2021.
- [68] O. Koutsos, F. F. Manziello, A. Clemente, and R. Sauleau, "Analysis, rigorous design, and characterization of a three-layer anisotropic transmitarray at 300 GHz," *IEEE Trans. Antennas Propag.*, vol. 70, no. 7, pp. 5437–5446, Jul. 2022.
- [69] S. Otto, A. Al-Bassam, A. Rennings, K. Solbach, and C. Caloz, "Transversal asymmetry in periodic leaky-wave antennas for bloch impedance and radiation efficiency equalization through broadside," *IEEE Trans. Antennas Propag.*, vol. 62, no. 10, pp. 5037–5054, Oct. 2014.
- [70] A. Al-Bassam, S. Otto, D. Heberling, and C. Caloz, "Analytical formulas for frequency-unbalanced periodic leaky-wave antennas," in *Proc. Photonics Electromagn. Res. Symp. - Spring*, Rome, Italy, 2019, pp. 1236–1242.
- [71] F. Mesa, R. Rodriguez-Berral, and F. Medina, "Unlocking complexity using the ECA: The equivalent circuit model as an efficient and physically insightful tool for microwave engineering," *IEEE Microw. Mag.*, vol. 19, no. 4, pp. 44–65, Jun. 2018.
- [72] R. Munson, "Conformal microstrip antennas and microstrip phased arrays," *IEEE Trans. Antennas Propag.*, vol. 22, no. 1, pp. 74–78, Jan. 1974.
- [73] A. Derneryd, "Linearly polarized microstrip antennas," *IEEE Trans. Antennas Propag.*, vol. 24, no. 6, pp. 846–851, Nov. 1976.
- [74] L. Lewin, "Radiation from discontinuities in strip-line," *Proc. Inst. Elect. Eng. C, Monographs*, vol. 107, no. 12, pp. 163–170, Sep. 1960.
- [75] L. Lewin, "Spurious radiation from microstrip," *Proc. Inst. Elect. Eng. U.K.*, vol. 125, no. 7, p. 633–642, Jul. 1978.
- [76] H. Sobal, "Radiation conductance of open-circuit microstrip (Correspondence)," *IEEE Trans. Microw. Theory Techn.*, vol. 19, no. 11, pp. 885–887, Nov. 1971.
- [77] B. Sievert, J. T. Svejda, J. Witteimer, N. Pohl, D. Erni, and A. Rennings, "Equivalent circuit model separating dissipative and radiative losses for the systematic design of efficient microstrip-based on-chip antennas," *IEEE Trans. Microw. Theory Techn.*, vol. 69, no. 2, pp. 1282–1294, Feb. 2021.
- [78] B. Sievert, D. Erni, and A. Rennings, "Resonant antenna periodically loaded with series capacitances for enhanced radiation efficiency," in *Proc. 12th Ger. Microw. Conf.*, Stuttgart, Germany, 2019, pp. 20–23.
- [79] D. B. Brück, "The radiation of a hertzian dipole over a coated conductor," *Cruft Lab., Harvard Univ., Cambridge, MA, USA, Tech. Rep. 172*, May 1953.
- [80] G. Tsandoulas, "Excitation of a grounded dielectric slab by a horizontal dipole," *IEEE Trans. Antennas Propag.*, vol. 17, no. 2, pp. 156–161, Mar. 1969.
- [81] S. Shastri and A. Kumar, "Dipole over a dielectric-coated conducting plane," *IETE J. Res.*, vol. 31, no. 1, pp. 12–19, Jan. 1985.
- [82] A. Derneryd, "A theoretical investigation of the rectangular microstrip antenna element," *IEEE Trans. Antennas Propag.*, vol. 26, no. 4, pp. 532–535, Jul. 1978.
- [83] B. Sievert, J. T. Svejda, D. Erni, and A. Rennings, "Spherical mm-Wave/THz antenna measurement system," *IEEE Access*, vol. 8, pp. 89680–89691, 2020.

- [84] H. Zhang and A. Shamim, "Tackling the issues of millimeter-wave on-chip antenna measurements," in *Proc. 13th Eur. Conf. Antennas Propag. (EuCAP)*, Krakow, Poland, 2019, pp. 1–5.
- [85] D. Titz, F. Ferrero, and C. Luxey, "Development of a millimeter-wave measurement setup and dedicated techniques to characterize the matching and radiation performance of probe-fed antennas," *IEEE Antennas Wireless Propag. Lett.*, vol. 54, no. 4, pp. 188–203, Aug. 2012.
- [86] L. Boehm, M. Hitzler, F. Roos, and C. Waldschmidt, "Probe influence on integrated antenna measurements at frequencies above 100 GHz," in *Proc. 46th Eur. Microw. Conf.*, Oct. 2016, pp. 552–555.
- [87] S.-K. Yong, P. Xia, and A. Valdes-Garcia, *60 GHz Technology for Gbps WLAN and WPAN*. Hoboken, NJ, USA: Wiley, 2010.
- [88] H. T. Friis, "A note on a simple transmission formula," *Proc. IRE*, vol. 34, no. 5, pp. 254–256, May 1946.
- [89] R. C. Qiu and I-Tai Lu, "Multipath resolving with frequency dependence for wide-band wireless channel modeling," *IEEE Trans. Veh. Technol.*, vol. 48, no. 1, pp. 273–285, Feb. 1998.
- [90] G. L. Turin, "Communication through noisy, random-multipath channels," Ph.D. dissertation, Dept. Elect. Eng., Massachusetts Inst. Technol., Cambridge, MA, USA, 1956.
- [91] G. L. Turin, "Communication through noisy, random-multipath channels," *IRE Nat. Conv. Rec.*, vol. 4, pp. 154–166, Mar. 1956.
- [92] G. L. Turin, F. D. Clapp, T. L. Johnston, S. B. Fine, and D. Lavry, "A statistical model of urban multipath propagation," *IEEE Trans. Veh. Technol.*, vol. 21, no. 1, pp. 1–9, Feb. 1972.
- [93] R. Price and P. E. Green, "A communication technique for multipath channels," *Proc. IRE*, vol. 46, no. 3, pp. 555–570, Mar. 1958.
- [94] H. Hashemi, "The indoor radio propagation channel," *Proc. IEEE*, vol. 81, no. 7, pp. 943–968, Jul. 1993.
- [95] H. Hashemi, "Simulation of the urban radio propagation channel," *IEEE Trans. Veh. Technol.*, vol. 28, no. 3, pp. 213–225, Aug. 1979.
- [96] R. Ganesh and K. Pahlavan, "Statistical modeling and computer simulation of indoor radio channel," *Proc. Inst. Elect. Eng.*, vol. 138, pp. 153–161, Aug. 1991.
- [97] H. Suzuki, "A statistical model for urban radio propagation," *IEEE Trans. Commun.*, vol. 25, no. 7, pp. 673–680, Jul. 1977.
- [98] A. A. M. Saleh and R. Valenzuela, "A statistical model for indoor multipath propagation," *IEEE J. Sel. Areas Commun.*, vol. 5, no. 2, pp. 128–137, Feb. 1987.
- [99] T. S. Rappaport, S. Y. Seidel, and K. Takamizawa, "Statistical channel impulse response models for factory and open plan building radio communicate system design," *IEEE Trans. Commun.*, vol. 39, no. 5, pp. 794–807, May 1997.
- [100] Z. Yun and M. F. Iskander, "Ray tracing for radio propagation modeling: Principles and applications," *IEEE Access*, vol. 3, pp. 1089–1100, 2015.
- [101] C. Lim, M. Lee, R. Burkholderet, J. Volakis, and R. Marhefka, "60 GHz indoor propagation studies for wireless communications based on a ray-tracing method," *EURASIP J. Wireless Commun. Netw.*, vol. 7, no. 1, pp. 1687–1699, Jan. 2007.
- [102] T. S. Rappaport and S. Sandhu, "Radio-wave propagation for emerging wireless personal-communication systems," *IEEE Antennas Propag. Mag.*, vol. 36, no. 5, pp. 14–24, Oct. 1994.
- [103] M. Born and E. Wolf, *Principles of Optics: Electromagnetic Theory of Propagation, Interference and Diffraction of Light*, 7th ed. Cambridge, U.K.: Cambridge Univ. Press, 1999.
- [104] J. B. Keller, "Geometrical theory of diffraction," *J. Opt. Soc. Amer.*, vol. 32, no. 2, pp. 116–130, Feb. 1962.
- [105] H. Ling, R.-C. Chou, and S.-W. Lee, "Shooting and bouncing rays: Calculating the RCS of an arbitrarily shaped cavity," *IEEE Trans. Antennas Propag.*, vol. 37, no. 2, pp. 194–205, Feb. 1989.
- [106] M. F. Catedra, J. Perez, F. Saez de Adana, and O. Gutierrez, "Efficient ray-tracing techniques for three-dimensional analyses of propagation in mobile communications: Application to picocell and microcell scenarios," *IEEE Antennas Propag. Mag.*, vol. 40, no. 2, pp. 15–28, Apr. 1998.
- [107] F. A. Agelet, F. P. Fontan, and A. Formella, "Fast ray tracing for microcellular and indoor environments," *IEEE Trans. Magn.*, vol. 33, no. 2, pp. 1484–1487, Mar. 1997.
- [108] G. E. Athanasiadou, A. R. Nix, and J. P. McGeehan, "A microcellular ray-tracing propagation model and evaluation of its narrow-band and wide-band predictions," *IEEE J. Sel. Areas Commun.*, vol. 18, no. 3, pp. 322–335, Mar. 2000.
- [109] K. Rizk, J.-F. Wagen, and F. Gardiol, "Two-dimensional ray-tracing modeling for propagation prediction in microcellular environments," *IEEE Trans. Veh. Technol.*, vol. 46, no. 2, pp. 508–518, May 1997.
- [110] N. C. Goncalves and L. M. Correia, "A propagation model for urban microcellular systems at the UHF band," *IEEE Trans. Veh. Technol.*, vol. 49, no. 2, pp. 1294–1302, Jul. 2000.
- [111] S. Y. Seidel and T. S. Rappaport, "Site-specific propagation prediction for wireless in-building personal communication system design," *IEEE Trans. Veh. Technol.*, vol. 43, no. 4, pp. 879–891, Nov. 1994.
- [112] D. I. Laurenson, S. McLaughlin, and A. U. H. Sheikh, "The application of ray tracing and the geometrical theory of diffraction to indoor channel modelling," in *Proc. IEEE Glob. Telecommun. Conf. (GLOBECOM)*, Houston, TX, USA, 1993, pp. 1242–1246.
- [113] K. A. Remley, H. R. Anderson, and A. Weissnar, "Improving the accuracy of ray-tracing techniques for indoor propagation modeling," *IEEE Trans. Veh. Technol.*, vol. 49, no. 6, pp. 2350–2358, Nov. 2000.
- [114] C.-F. Yang, B.-C. Wu, and C.-J. Ko, "A ray-tracing method for modeling indoor wave propagation and penetration," *IEEE Trans. Antennas Propag.*, vol. 46, no. 6, pp. 907–919, Jun. 1998.
- [115] M. Peter, W. Keusgen, and R. Felbecker, "Measurement and ray-tracing simulation of the 60 GHz indoor broadband channel: Model accuracy and parameterization," in *Proc. 2nd Eur. Conf. Antennas Propag.*, Edinburgh, U.K., 2007, pp. 1–8.
- [116] J. Webber, H. Kamoda, N. Kukutsu, and T. Kumagai, "Millimeter-wave wireless communication in a data center cabinet with adaptive control of propagation," in *Proc. 21st Asia-Pacific Conf. Commun.*, Kyoto, Japan, 2007, pp. 272–277.
- [117] P. Beckmann and A. Spizzichino, *The Scattering of Electromagnetic Waves from Rough Surfaces*. Norwood, MA, USA: Artech House Inc., 1983.
- [118] S. Priebe et al., "Non-specular scattering modeling for THz propagation simulations," in *Proc. 5th Eur. Conf. Antennas Propag.*, Rome, Italy, 2011, pp. 1–5.
- [119] F. Sheikh, D. Lessy, and T. Kaiser, "A novel ray-tracing algorithm for non-specular diffuse scattered rays at terahertz frequencies," in *Proc. First Int. Workshop Mobile THz Syst.*, Duisburg, Germany, 2018, pp. 1–6.
- [120] V. Degli Esposti et al., "An advanced field prediction model including diffuse scattering," *IEEE Trans. Antennas Propag.*, vol. 52, no. 7, pp. 1717–1728, Jul. 2004.
- [121] R. Piesiewicz, C. Jansen, D. Mittleman, T. Kleine-Ostmann, M. Koch, and T. Kürner, "Scattering analysis for the modeling of THz communication systems," *IEEE Trans. Antennas Propag.*, vol. 55, no. 11, pp. 3002–3009, Nov. 2007.
- [122] F. Sheikh, Y. Zhang, Y. Zanteh, I. Mabrouk, M. Hasan, and T. Kaiser, "A ray tracing approach to the scattering of electromagnetic waves from random rough surfaces at terahertz frequencies," in *Proc. 45th Int. Conf. Infrared, Millimeter, THz Waves*, Buffalo, NY, USA, 2020, pp. 1–1.
- [123] F. Sheikh, B. Salah, D. Lessy, and T. Kaiser, "Unexplored aspects in THz ray-tracing," in *Proc. 4th Int. Workshop Mobile THz Syst.*, Essen, Germany, 2021, pp. 1–6.
- [124] F. Sheikh and T. Kaiser, "Angle of arrival and angle of departure analysis in scattering environment for THz wireless links," in *Proc. IEEE Int. Symp. Antennas Propag. USNC-URSI Radio Sci. Meeting*, Denver, CO, USA, 2022, pp. 1688–1689.
- [125] F. Sheikh et al., "Scattering and roughness analysis of indoor materials at frequencies from 750 GHz to 1.1 THz," *IEEE Trans. Antennas Propag.*, vol. 69, no. 11, pp. 7820–7829, Nov. 2021.
- [126] F. Sheikh, Y. Zantah, and T. Kaiser, "Exploring ping pong channels at THz frequencies," *Proc. Antenna Meas. Techn. Assoc. Symp.*, Daytona Beach, FL, USA, 2021, pp. 1–6.
- [127] Y. Wu, J. Kokkonieni, C. Han, and M. Juntti, "Interference and coverage analysis for terahertz networks with indoor blockage effects and line-of-sight access point association," *IEEE Trans. Wireless Commun.*, vol. 20, no. 3, pp. 1472–1486, Mar. 2021.
- [128] L. Xiong, H. Miao, and Z. Yao, "Human body model for channel characterization based on ray-tracing," *Int. J. Antennas Propag.*, vol. 1, pp. 1–17, Oct. 2020.
- [129] A. Prokscha, F. Sheikh, D. Lessy, N. A. Ali, and T. Kaiser, "Multi-disciplinary data fusion for THz ray-tracing," in *Proc. 16th Eur. Conf. Antennas Propag.*, Madrid, Spain, 2022, pp. 1–5.

- [130] A. Prokscha, F. Sheikh, D. Lessy, and T. Kaiser, "Portable device-centric human postures for modeling reliable THz channels," in *Proc. 5th Int. Workshop Mobile THz Syst.*, Duisburg, Germany, 2022, pp. 1–5.
- [131] N. Dreyer and T. Kürner, "An analytical raytracer for efficient D2D path loss predictions," in *Proc. 13th Eur. Conf. Antennas Propag.*, Krakow, Poland, 2019, pp. 1–5.
- [132] T. Doeker, P. Reddy Samala, P. S. Negi, A. Rajwade, and T. Kürner, "Angle of arrival and angle of departure estimation using compressed sensing for terahertz communications," in *Proc. 15th Eur. Conf. Antennas Propag.*, Dusseldorf, Germany, 2021, pp. 1–5.
- [133] B. Addon, X-Muscle System 3.0, Accessed: Oct. 2022. [Online]. Available: <https://blendermarket.com/products/x-muscle-system>
- [134] K. Guan et al., "Scenario modules and ray-tracing simulations of millimeter wave and terahertz channels for smart rail mobility," in *Proc. 11th Eur. Conf. Antennas Propag.*, Paris, France, 2017, pp. 113–117.
- [135] J. Jebramcik, J. Wagner, N. Pohl, I. Rolfes, and J. Barowski, "Millimeter wave material measurements for building entry loss models above 100 GHz," in *Proc. 15th Eur. Conf. Antennas Propag.*, Dusseldorf, Germany, 2021, pp. 1–5.
- [136] K. Nallappan, Y. Cao, G. Xu, H. Guerboukha, C. Nerguizian, and M. Skorobogatiy, "Dispersion-limited versus power-limited terahertz communication links using solid core subwavelength dielectric fibers," *Photon. Res.*, vol. 8, no. 11, pp. 1757–1775, Oct. 2020.
- [137] J. Wang, C.-X. Wang, J. Huang, and H. Wang, "A novel 3D space-time-frequency non-stationary channel model for 6 G THz indoor communication systems," in *Proc. IEEE Wireless Commun. Netw. Conf.*, Seoul, Korea, 2020, pp. 1–7.
- [138] A. Moldovan, M. A. Ruder, I. F. Akyildiz, and W. H. Gerstacker, "LOS and NLOS channel modeling for terahertz wireless communication with scattered rays," in *Proc. IEEE Globecom Workshops*, Austin, TX, USA, 2014, pp. 1–7.
- [139] E. Björnson and L. Sanguinetti, "Power scaling laws and near-field behaviors of massive MIMO and intelligent reflecting surfaces," *IEEE Open J. Commun. Soc.*, vol. 1, pp. 1306–1324, 2020.
- [140] E. Budiarto, N.-W. Pu, S. Jeong, and J. Bokor, "Near-field propagation of terahertz pulses from a large-aperture antenna," *Opt. Lett.*, vol. 23, no. 3, pp. 213–215, Feb. 1998.
- [141] J. Hu, M. Jiang, H. Shao, and Z. Nie, "Solving multi-scale electromagnetic problems by domain decomposition based integral equation method," in *Proc. IEEE Asia-Pacific Conf. Antennas Propag.*, Austin, TX, USA, 2012, pp. 96–97.
- [142] F. Weinmann, "Ray tracing with PO/PTD for RCS modeling of large complex objects," *IEEE Trans. Antennas Propag.*, vol. 54, no. 6, pp. 1797–1806, Jun. 2006.
- [143] M. A. A. Moneum, Z. Shen, J. L. Volakis, and O. Graham, "Hybrid PO-MoM analysis of large axi-symmetric radomes," *IEEE Trans. Antennas Propag.*, vol. 49, no. 12, pp. 1657–1666, Dec. 2001.
- [144] V. Degli-Esposti, E. M. Vitucci, M. di Renzo, and S. A. Tretyakov, "Reradiation and scattering from a reconfigurable intelligent surface: A general macroscopic model," *IEEE Trans. Antennas Propag.*, early access, Feb. 14, 2022, doi: [10.1109/TAP.2022.3149660](https://doi.org/10.1109/TAP.2022.3149660).
- [145] V. Degli-Esposti et al., "Ray-tracing-Based mm-wave beamforming assessment," *IEEE Access*, vol. 2, pp. 1314–1325, 2014.
- [146] D. M. Sullivan, *Electromagnetic Simulation Using the FDTD Method*. Hoboken, NJ, USA: Wiley, 2013.
- [147] A. R. Hall, *Generalized Method of Moments*. London, U.K.: Oxford Univ. Press, 2005.
- [148] K. Dovelos, S. D. Assimonis, H. Quoc Ngo, B. Bellalta, and M. Matthaiou, "Intelligent reflecting surfaces at terahertz bands: Channel modeling and analysis," in *Proc. IEEE Int. Conf. Commun. Workshops*, Montreal, QC, Canada, 2021, pp. 1–6.
- [149] S. Vogt, J. Jebramcik, O. Garten, J. Barowski, and I. Rolfes, "Investigation on optical methods for multi scale electromagnetic simulations," in *Proc. 12th German Microw. Conf.*, Stuttgart, Germany, 2019, pp. 28–31.
- [150] S. Vogt, O. Garten, J. Jebramcik, J. Barowski, and I. Rolfes, "Asymptotic simulation methods as forward models in multilayer material characterization applications," in *Proc. IEEE MTT-S Int. Microw. Workshop Ser. Adv. Mater. Processes RF THz Appl.*, Bochum, Germany, 2019, pp. 109–111.
- [151] S. Orlov and U. Peschel, "Complex source beam: A tool to describe highly focused vector beams analytically," *Phys. Rev. A*, vol. 82, no. 6, Dec. 2010, Art. no. 063820.
- [152] C. Ruchert, C. Vicario, and C. P. Hauri, "Spatiotemporal focusing dynamics of intense supercontinuum THz pulses," *Phys. Rev. Lett.*, vol. 110, no. 12, pp. 123902 1–5, Mar. 2013.
- [153] C. A. Balanis, *Advanced Engineering Electromagnetics*. Hoboken, NJ, USA: Wiley, 2012.
- [154] O. Garten, J. Barowski, and I. Rolfes, "Considerations regarding simulator design for electromagnetic measurement systems," in *Proc. IEEE Int. Conf. Comput. Electromagn.*, Singapore, 2020, pp. 17–18.
- [155] G. Carli, E. Martini, and S. Maci, "Space decomposition method by using complex source expansion," in *Proc. IEEE Antennas Propag. Soc. Int. Symp.*, San Diego, CA, USA, 2008, pp. 1–4.
- [156] K. Guan et al., "On millimeter wave and THz mobile radio channel for smart rail mobility," *IEEE Trans. Veh. Technol.*, vol. 66, no. 7, pp. 5658–5674, Jul. 2017.
- [157] V. Petrov, J. Kokkonen, D. Moltchanov, J. Lehtomäki, M. Juntti, and Y. Koucheryavy, "The impact of interference from the side lanes on mmWave/THz band V2V communication systems with directional antennas," *IEEE Trans. Veh. Technol.*, vol. 67, no. 6, pp. 5028–5041, Jun. 2018.



FAWAD SHEIKH (Member, IEEE) received the Dr.-Ing. degree from the University of Duisburg-Essen, Duisburg, Germany, in 2019. He is currently a Senior Postdoctoral Researcher with the Institute of Digital Signal Processing (DSV). From 2006 to 2011, he worked on cellular and IT service management projects with Fraunhofer IMS, Duisburg, Germany, KlickTel AG, Essen, Germany, Vodafone D2 GmbH, Düsseldorf, Germany, and Deutsche Telekom AG, Deutschland, Germany, respectively. From January 2012 to May 2017, he

was associated with DSV, University of Duisburg-Essen, Duisburg, Germany, for the project Wireless 100 Gb/s and beyond. Since June 2017, he has been with project Mobile MAtERIAL TransEiver. He is a coordinator of the IEEE International Workshop Series on Mobile Terahertz Systems started in 2018 and CEO of The Mobile THz Company UG, offering concept designs and performance analyses of mobile THz systems. His research interests include systems and components in THz band communications, measurement and modeling of mobile radio channels, massive MIMO systems, mobile material characterization and localization, and THz sensing for monitoring plants, fruits as well as insects within the frequency range of 250 GHz to 5 THz.



ANDREAS PROKSCHA (Student Member, IEEE) received the M.Sc. degree in electrical engineering from the University of Duisburg-Essen, Duisburg, Germany, in 2019. He is currently working toward the Ph.D. degree with the Institute of Digital Signal Processing (DSV). Since 2020, he has been with ID4us GmbH, Duisburg, Germany, RFID Centric Company. In 2021, he joined DSV. Since June 2021, he has been involved in multiple research projects with main focus on the project mobile MAtERIAL TransEiver. His research interests include 3-D environment modeling with applying human kinematics based on

inertial sensors, investigating human digital twins within THz communication channels and human medical related applications in millimeter and THz frequencies respectively.



JOHANNES M. ECKHARDT (Student Member, IEEE) was born in Braunschweig, Germany, in 1992. He received the Dipl.-Ing. degree in electrical engineering from Technische Universität Dresden, Dresden, Germany, and the master's degree from Ecole Centrale Paris, Paris, France, in 2017, respectively. He is currently working toward the Ph.D. degree with the Department of Mobile Radio Systems, Institute for Communications Technology, Technische Universität Braunschweig, Braunschweig, Germany. His research interests include

channel measurements and modeling, link-level simulations and interference studies in complex scenarios for multi gigabit communication systems at THz frequencies.



TOBIAS DOEKER (Student Member, IEEE) was born in Haltern, Germany, in 1994. He received the B.Sc. degree from Hamburg University of Applied Science Hamburg, Germany, in 2017, and the M.Sc. degree in electrical engineering with a focus on communications technology from Technische Universität Braunschweig, Braunschweig, Germany, in 2019, where he is currently working toward the Ph.D. degree. From 2013 to 2019, he was a student trainee with Lufthansa Technik AG, Hamburg, Germany. In November 2019, he joined

the Institute for Communications Technology with Technische Universität Braunschweig as a Researcher. His research interests include THz communications, radio channel measurements and characterization, and device discovery for multi gigabit indoor communication at 300 GHz.



NAVEED A. ABBASI (Member, IEEE) received the bachelor's degree in electrical engineering from Air University, Islamabad, Pakistan, in 2007, the master's degree from Northwestern Polytechnical University, Xi'an, China, in 2010, and the Ph.D. degree from Koc University, Istanbul, Turkey, in 2018. He is currently a Postdoctoral Fellow with the WiDeS lab, University of Southern California, Los Angeles, CA, USA. His research interests include channel sounder design, measurements and modeling for various wireless communication

bands including THz, mm-wave and Wi-fi, the applications of machine learning towards wireless communication, molecular, and nano-scale communication.



JORGE GOMEZ-PONCE (Student Member, IEEE) received the B.Sc. degree in electronics and telecommunications engineering and the master's degree in telecommunications from Escuela Superior Politécnica del Litoral Guayaquil, Ecuador, in 2011 and 2015, respectively, and the MSEE degree in electrical engineering from the University of Southern California, Los Angeles, CA, USA, in 2019, where he is currently working toward the Ph.D. candidate in electrical engineering. His research interests include

statistical and ray-tracer modeling for wireless communication channels e.g., Wi-Fi, UAV, sub-7 GHz, mm-wave, and THz, RF systems design and implementation with DSP/FPGA systems, estimation theory and machine learning applied to wireless communications, and cognitive radio systems.



BENEDIKT SIEVERT (Member, IEEE) was born in Krefeld, Germany. He received the B.Sc. and M.Sc. degrees in electrical engineering/high-frequency systems from the University of Duisburg-Essen, Duisburg, Germany, in 2017 and 2019, respectively. Since 2017, he has been a member of the Laboratory of General and Theoretical Electrical Engineering, University of Duisburg-Essen. His research interests include mm-wave on-chip antennas, electromagnetic metamaterials, theoretical, and computational electromagnetics.



JAN TARÓ SVEJDA (Member, IEEE) received the B.Sc. degree from the University of Applied Science, Düsseldorf, Germany, in 2008, and the M.Sc. and Dr.-Ing. degrees in electrical engineering and information technology from the University of Duisburg-Essen, Duisburg, Germany, in 2013 and 2019, respectively. He started the electrical engineering career with the University of Applied Science. He is currently a Research Assistant with the Department of General and Theoretical Electrical Engineering, University of Duisburg-Essen,

where he is also involved in teaching several lectures and courses mainly in the field of electrical engineering. His research interests include all aspects of theoretical and applied electromagnetics, X-nuclei based magnetic resonance imaging, and focusing on medical applications, electromagnetic metamaterials, and scientific computing methods.



ANDREAS RENNINGS (Member, IEEE) received the Dipl.-Ing. and Dr.-Ing. degrees from the University of Duisburg-Essen, Duisburg, Germany, in 2000 and 2008, respectively. He studied electrical engineering with the University of Duisburg-Essen. He carried out his diploma work during a stay with the University of California, Los Angeles, CA, USA. From 2006 to 2008, he was with IMST GmbH, Kamp-Lintfort, Germany, where he was an RF engineer. Since then, he has been a Senior Scientist and Principal Investigator with the

Laboratory for General and Theoretical Electrical Engineering, University of Duisburg-Essen. His research interests include all aspects of theoretical and applied electromagnetics, with a focus on medical applications and on-chip millimeter-wave/THz antennas. He was the recipient of the several awards, including a Student Paper Prize at the 2005 IEEE Antennas and Propagation Society International Symposium and the VDE-Promotionspreis 2009 for the dissertation.



JAN BAROWSKI (Senior Member, IEEE) was born in Bochum, Germany, in 1988. He received the B.Sc. and M.Sc. degrees in electrical engineering and the Dr.Eng. degree (with honors) in electrical engineering from Ruhr University Bochum, Bochum, Germany, in 2010, 2012, and 2017, respectively. Since 2012, he has been with the Institute of Microwave Systems, headed by Ilona Rolfes, Ruhr University Bochum, as a Research Assistant. He is currently a Postdoctoral Research Scientist with the Institute of Microwave

Systems. His research interests include radar signal processing, radar imaging, and material characterization techniques. Dr. Barowski was the recipient of the IEEE Antennas and Propagation Society Doctoral Research Grant in 2016 and the IEEE MTT IWMS-AMP Best Student Paper Award in 2017, U.R.S.I. Germany Sections Young Scientist Award and the German Association for Electrical, Electronic and Information Technologies (VDE) Award for the Doctoral dissertation, in 2018.



CHRISTIAN SCHULZ (Member, IEEE) received the Dipl. Ing. and Dr. Ing. degrees in electrical engineering from Ruhr University Bochum, Bochum, Germany, in 2009 and 2016, respectively. From 2010 to 2016, he was a Research Assistant with the Institute of Microwave Systems, Ruhr University Bochum, where he has been a Postdoctoral Researcher since 2016. His research interests include 3-D electromagnetic field simulations, plasma diagnostics, radar systems, and antenna design. Dr. Schulz was the recipient of the IEEE Antennas and

Propagation Society Doctoral Research Award in 2014, the IEEE Microwave Theory and Techniques Society (IEEE MTT-S) Graduate Fellowship Award in 2015, and the Gert Massenber Award for Doctoral dissertation in 2017.



ILONA ROLFES (Senior Member, IEEE) received the Dipl. Ing. and Dr. Ing. degrees in electrical engineering from Ruhr University Bochum, Bochum, Germany, in 1997 and 2002, respectively. From 1997 to 2005, she was with the High Frequency Measurements Research Group, Ruhr University Bochum, as a Research Assistant. From 2005 to 2009, she was a Junior Professor with the Department of Electrical Engineering, Leibniz University Hannover, Hannover, Germany, where she became the Head of the Institute of Radio frequency and

Microwave Engineering in 2006. Since 2010, she has been leading the Institute of Microwave Systems, Ruhr University Bochum. Her research interests include high-frequency measurement methods for vector network analysis, material characterization, noise characterization of microwave devices, sensor principles for radar systems. Dr. Rolfes is currently a member of the Executive Committee of the IEEE MTT-S International Microwave Workshop Series on Advanced Materials and Processes. She is also a Board Member of the German IEEE MTT-AP Chapter and the German Commission for Electromagnetic Metrology of U.R.S.I.



DANIEL ERNI (Senior Member, IEEE) received the Diploma in electrical engineering from the University of Applied Sciences Rapperswil, Rapperswil, Switzerland, in 1986, and the Diploma in electrical engineering and the Ph.D. degree in laser physics from ETH Zürich, Zürich, Switzerland, in 1990 and 1996, respectively. Since 1990, he has been with the Laboratory for Electromagnetic Fields and Microwave Electronics, ETH Zürich, Zürich, Switzerland. From 1995 to 2006, he was the Founder and the Head of the Communication

Photonics Group, ETH Zürich. Since October 2006, he has been a Full Professor with the Department of General and Theoretical Electrical Engineering, University of Duisburg-Essen, Duisburg, Germany. Between 2017 and 2018 he joined the Institute of Electromagnetic Fields (IEF), ETH Zürich, as a Visiting Professor. He is also a cofounder of the spinoff company airCode, Hamm, Germany, working on flexible printed RFID Technology. His research interests include optical interconnects, nanophotonics, plasmonics, advanced solar cell concepts, optical and electromagnetic metamaterials, RF, mm-wave and THz engineering, chipless flexible RFIDs, biomedical engineering, bioelectromagnetics, marine electromagnetics, computational electromagnetics, multiscale and multiphysics modeling, numerical structural optimization, and science and technology studies. Dr. Erni is a Fellow of the Electromagnetics Academy and a member of the Center for Nanointegration Duisburg-Essen; Materials Chain, Flagship Program of the University Alliance Ruhr; the Swiss Physical Society; the German Physical Society; and the Optical Society of America.



ANDREAS F. MOLISCH (Fellow, IEEE) received the Ph.D. and Habilitation degrees from Technical University Vienna, Vienna, Austria, in 1994 and 1999, respectively. He spent the next 10 years in industry with FTW, AT&T (Bell) Laboratories, and Mitsubishi Electric Research Labs, Cambridge, MA, USA, where he rose to the position of Chief Wireless Standards Architect. In 2009, he joined the University of Southern California (USC), Los Angeles, CA, USA, as Professor, and founded the Wireless Devices and Systems (WiDeS) Group. In

2017, he was appointed to the Solomon Golomb Andrew and Erna Viterbi Chair. His research interests include wireless propagation channels, wireless systems design and their interaction, wireless channel measurement, modeling for 5G and beyond 5G systems, joint communication-caching-computation, hybrid beamforming, UWB/TOA based localization, and novel modulation/multiple access methods. He has authored or coauthored five books, among them the textbook *Wireless Communications*, third edition in 2022, 22 book chapters, 300 journal papers, and 400 conference papers. He is also an inventor of 70 granted and more than ten pending patents, and coauthor of some 70 standards contributions. His work has been cited more than 60,000 times, his h-index is >100, and he is a Clarivate Highly Cited Researcher. Dr. Molisch is an editor of a number of journals and special issues; General Chair, Technical Program Committee Chair, or Symposium Chair of multiple international conferences; and a Chairperson of various international standardization groups. He is a Fellow of the National Academy of Inventors, AAAS, and IET; IEEE Distinguished Lecturer; and a member of the Austrian Academy of Sciences. He was a recipient of numerous awards, among them the IET Achievement Medal, Technical Achievement Awards of IEEE Vehicular Technology Society (Evans Avant-Garde Award) and IEEE Communications Society (Edwin Howard Armstrong Award), Technical Field Award of IEEE for Communications, and Eric Sumner Award.



THOMAS KÜRNER (Fellow, IEEE) received the Dipl.-Ing. degree in electrical engineering and the Dr.-Ing. degree from the University of Karlsruhe, Karlsruhe, Germany, in 1990 and 1993, respectively. From 1990 to 1994, he was with the Institut für Höchstfrequenztechnik und Elektronik, University of Karlsruhe, working on wave propagation modelling, radio channel characterisation, and radio network planning. From 1994 to 2003, he was with the Radio Network Planning Department, the headquarters of the GSM 1800 and UMTS Oper-

ator E-Plus Mobilfunk GmbH & Co KG, Düsseldorf, where he was team manager, radio network planning support, responsible for radio network planning tools, algorithms, processes, and parameters from 1999 to 2003. Since 2003, he has been a Full University Professor of mobile radio systems with the Technische Universität Braunschweig, Braunschweig, Germany. In 2012, he was a Guest Lecturer with Dublin City University within the Telecommunications Graduate Initiative in Ireland. He is currently chairing the IEEE 802.15 Standing Committee THz. He was also the Chair of IEEE 802.15.3 d TG 100 G, which developed the worldwide first wireless communications standard operating at 300 GHz. He was a project coordinator of the H2020-EU-Japan project ThoR TeraHertz End-to-End Wireless Systems Supporting Ultra-High Data Rate Applications and a coordinator of the German DFG-Research Unit FOR 2863 Meteraom Metrology for THz Communications. In 2019 and 2022, he was the recipient of the Neal-Shephard Award of the IEEE Vehicular Technology Society. From 2016 to 2021, he was a member of the Board of Directors of the European Association on Antennas and Propagation and from 2020 to 2022, a Distinguished Lecturer of IEEE Vehicular Technology Society.



THOMAS KAISER (Senior Member, IEEE) received the Diploma in electrical engineering from Ruhr-University Bochum, Bochum, Germany, in 1991, and the Ph.D. (with distinction) and German Habilitation degrees in electrical engineering from Gerhard Mercator University, Duisburg, Germany, in 1995 and 2000, respectively. From 1995 to 1996, he spent a research leave with the University of Southern California, Los Angeles, CA, USA, which was grant-aided by the German Academic Exchange Service. From April 2000 to March

2001, he was the Head of the Department of Communication Systems, Gerhard Mercator University, and from April 2001 to March 2002, he was the Head of the Department of Wireless Chips and Systems, Fraunhofer Institute of Microelectronic Circuits and Systems, Duisburg, Germany. From April 2002 to July 2006, he was Co-Leader of the Smart Antenna Research Team, University of Duisburg-Essen, Duisburg, Germany. In summer 2005, he joined the Smart Antenna Research Group, Stanford University, Stanford, CA, USA, and in winter 2007, he joined the Department of Electrical Engineering, Princeton University, Princeton, NJ, USA, as a Visiting Professor. From 2006 to 2011, he headed the Institute of Communication Technology, Leibniz University of Hannover, Hannover, Germany. He currently heads the Institute of Digital Signal Processing, University of Duisburg-Essen, and is the founder of three startup companies and CEO of ID4us GmbH, an RFID centric company. He is the author and coauthor of more than 300 papers in international journals and conference proceedings and two books titled *Ultra Wideband Systems With MIMO* (Wiley, 2010) and *Digital Signal Processing for Passive RFID* (Wiley, 2015). He is also a speaker of the Collaborative Research Center Mobile Material Characterization and Localization by Electromagnetic Sensing. Dr. Kaiser was the founding Editor-in-Chief of the e-letter of the IEEE Signal Processing Society and the General Chair of the IEEE International Conference on UltraWideBand in 2008, the International Conference on Cognitive Radio Oriented Wireless Networks and Communications in 2009, the IEEE Workshop on Cellular Cognitive Systems in 2014, and the IEEE Workshop Series on Mobile THz Systems started in 2018.